



## FP400P DASHCAM

### DESCRIPTION

Fleet Pins Dash Cam 400P has updated windscreen-mounted and cloud capability with 1080P front camera recording everything happening on the road. It also has a cabin view camera that helps in monitoring drivers and passengers.

### FEATURES

- HIGHLY INTEGRATED DESIGN
- DRIVER BEHAVIOUR MONITORING
- EVENT VIDEO TO CLOUD
- PANIC BUTTON
- 4G+WIFI
- HD VIDEO RESOLUTION
- LOCKED SIM/ SD CARD DESIGN
- GPS TRACKING
- ANDROID 8.1 GO
- OPEN I/O

### APPLICATION AREA

#### RIDE SHARING



#### TAXI OPERATIONS



#### COMMERCIAL FLEET



[WWW.FLEETPINS.COM](http://WWW.FLEETPINS.COM)

 520 200 5445

 6035 S Marin Ct Gilbert AZ 85298



## HARDWARE SPECIFICATION

ITEM	SPECIFICATION	REMARK
Wi-Fi	802.11 b/g/n	
Standard Version	GSM & WCDMA & 4G	GSM: 850/900/1800/1900 WCDMA: 85D/900/1900/2100 4G FDD: B1 B3 B5 B7 B8 B20 TDD: B38,B39,B40,B41
American Version	GSM & WCDMA & 4G	GSM: 850/900 1800/1900 WCDMA: B2 B4 B5 B8 FDD: B2 B3 B4 B5 B7 B12 B17 TDD: B38 B40 B41 (100M)
Note: The difference in Standard Version and American Version lies in hardware. It is recommended to debug by version.		
CPU		ARM Cortex A53 @1.4GHz
OS	Android	Android 8.1 GO
Flash Memory	RAM+ROM	LPDDR3 1GB+eMMC 16G
Front Camera	Forward recording	Built-in, AHD, 1080P, dynamic frame rate, 120° viewing angle
Detached camera	Detached camera	Detached camera, AHD, 720P dynamic frame rate, 100° viewing angle, night vision
GPS Module	GPS+BDS	Built-in ceramic antenna
G-Sensor	Accelerometer, Gyroscope	6 axis
MIC & Speaker	Built-in	
SD card	Max 128GB	
ACC	Ignition detection	
Relay	Immobilization	Remote engine cut-off
UART I/O(Extended I/O)	Open for RFID reader,Fuel sensor,Load sensor Temperature sensor	
SOS	Panic button	
Supply voltage	DC 12-24V	work for car, truck, bus, electric automobile etc.
External Battery	External Battery 450mAh	For emergency situation when car battery is disconnected
Dimension	109*69*52 mm	
Weight	225g	

[WWW.FLEETPINS.COM](http://WWW.FLEETPINS.COM)



520 200 5445



6035 S Marin Ct Gilbert AZ 85298